



# HP Jetdirect 3000w NFC/Wireless Direct Accessory

## Plug into simple, secure mobile printing

Bring greater agility and mobile productivity to your business. Easily set up and manage peer-to-peer printing with an accessory designed for select HP LaserJet Enterprise MFPs and printers,<sup>1,2</sup> while helping to protect enterprise data and systems.



## Print from mobile devices—simply

Make peer-to-peer printing easy for everyone on select HP LaserJet Enterprise MFPs and printers.<sup>1</sup> With the HP Jetdirect 3000w NFC/Wireless Direct Accessory, users can:<sup>2</sup>

- Deploy wireless direct printing and near field communication (NFC) touch-to-print technology on HP printers or MFPs in a few simple steps.<sup>1,2,3</sup> This accessory easily plugs into the Hardware Integration Pocket (HIP) or back USB port of your HP device.<sup>1,4</sup>
- Manage peer-to-peer printing at the device level, using the control panel or HP Embedded Web Server. Or apply changes fleet-wide using HP Web Jetadmin remote management software.<sup>5</sup>
- Save employees time and effort by making it easy to send print jobs from smartphones, tablets or laptop PCs that use a 2.4 GHz bandwidth from anywhere in the office. Add the option to print from NFC-enabled mobile devices—no network needed.<sup>2,3</sup>



**1. Plug accessory into printer**

**2. Find printer on device**

**3. Hit Print or walk up and print with just a touch**

## Go mobile and stay protected

Control device access and safeguard information from the start to finish of printing tasks:

- Documents are encrypted both in transit and on the printer or MFP.
- Protect your business information while giving users touch-to-print convenience. Print directly from mobile devices without accessing the corporate network.<sup>2,3</sup>

## Multiple options, easy control

Give employees the option to print directly from an array of mobile devices without hassle:<sup>2</sup>

- Easily print documents, emails, PDFs and more from an iPhone and iPad, as well as smartphones and tablets running iOS, Android™, Windows® 8 and 10, and Google™ Chrome™ operating systems—generally no setup or apps required.<sup>2</sup>
- Mobile devices can automatically connect to your printer or MFP, and then switch back to the corporate Wi-Fi network—or simply disconnect—when users walk away.<sup>2</sup>



## Product specifications

<b>Part number</b>	J8030A
<b>Connectivity</b>	802.11b/g wireless Ethernet; NFC; Hi-Speed USB 2.0
<b>Supported printers and MFPs</b>	HP LaserJet Enterprise M506 series, MFP M527 series, M604 series, M605 series, M606 series; HP Color LaserJet Enterprise M552 series, M553 series, MFP M577 series; For a complete list of supported devices, visit <a href="http://hp.com/go/jetdirect">hp.com/go/jetdirect</a>
<b>Network types</b>	802.11g wireless Ethernet
<b>Browsers supported</b>	Microsoft Internet Explorer 6.0 and higher; Mozilla 2.x and higher; Firefox 2.x and higher; Safari; Chrome
<b>Memory</b>	None (uses memory and storage in printer)
<b>Network operating systems<sup>6</sup></b>	Uses printer/MFP firmware. See the printer/MFP datasheet for compatible Network Operating Systems.
<b>Network protocols</b>	IPv4/IPv6: Apple Bonjour compatible, SNMPv1/v2c/v3, HTTP, HTTPS, FTP, Port 9100, LPD, IPP, Secure-IPP, WS Discovery, WS Print; IPv6: MLDv1, ICMPv6; IPv4: SLP, Telnet, IGMPv2, DHCP Server, AirPrint, GCP 2.0
<b>Security</b>	Management security: SNMPv3, SSL/TLS (HTTPS); Wireless network security: WPA2-Personal (WPA2-AES); administrator password; Plus: Same security protocols as attached printer/MFP
<b>Dimensions</b>	81 x 56 x 20 mm (3.2 x 2.2 x 0.8 in)
<b>Weight</b>	0.061 kg (0.13 lb)
<b>Packaged dimensions</b>	178 x 138 x 60 mm (7.0 x 5.4 x 2.4 in)
<b>Packaged weight</b>	0.266 kg (0.59 lb)
<b>What's in the box</b>	HP Jetdirect 3000w NFC/Wireless Direct Accessory; 2 mini USB cables; stand-alone plastic cover; Velcro kit; installation guide; warranty cards
<b>Warranty</b>	One-year replacement warranty
<b>Power specifications</b>	Host USB powered accessory, input voltage: 5 V, 500mA Power consumption: <sup>7</sup> 2.5 watts maximum
<b>Environmental ranges</b>	Recommended temperature: 0 to 40° C (32 to 104° F); Storage temperature: -40 to 70° C (-40 to 158° F); Humidity (operating and non-operating): 15 to 95% RH
<b>Standards and certifications</b>	Safety: EU (Low Voltage Directive 2006/95/EC), EN 60950-1: 2006 + A11:2009 + A1:2010 + A12:2011; US/Canada; UL listed EMC: EU (EMC Directive 2004/108/EC) EN 301 489-1 V1.9.2, EN 489-17 V2.1.1, US (FCC Title 47 CFR Part 15 Class B), Canada (ICES-003 Issue 5: 2012) Wireless telecommunications: EU (R&TTE Directive 1999/5/EC, EN 300 328, EN 62311, USA (FCC CFR 47 Part 15 Subpart C), Canada RSS-210

**Learn more at**  
[hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting)

### Notes

<sup>1</sup> HP 3000w NFC/Wireless Direct Accessory is compatible with select HP LaserJet Enterprise printers and MFPs with HP FutureSmart Firmware, introduced Spring 2015 and later. For a list of supported devices, see [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting).

<sup>2</sup> Feature is supported on select printers and may require purchase of an optional accessory. Mobile device needs to be connected directly to the Wi-Fi network of a wireless direct-capable MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. Learn more at [hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting).

<sup>3</sup> Requires a compatible NFC-printing-enabled mobile device. For a list of compatible NFC-printing-enabled mobile devices, see [hp.com/go/businessmobileprinting](http://hp.com/go/businessmobileprinting).

<sup>4</sup> When installed on a device with embedded wireless direct/NFC touch-to-print capabilities, the HP Jetdirect 3000w NFC/Wireless Direct Accessory will predominate and embedded capabilities will turn off.

<sup>5</sup> HP Web Jetadmin is available for download at [hp.com/go/webjetadmin](http://hp.com/go/webjetadmin). Universal device plug-in is offered with HP Web Jetadmin 10.3 SR4 and higher.

<sup>6</sup> Not all protocol and operating system combinations are supported. For more information refer to the support page at [hp.com/support/id3000w](http://hp.com/support/id3000w). Select the HP Jetdirect 3000w and then select HP Support and Drivers.

<sup>7</sup> Values subject to change. Power numbers are the highest values measured using all standard voltages. See [hp.com/support](http://hp.com/support) for current information.

**Sign up for updates**  
[hp.com/go/getupdated](http://hp.com/go/getupdated)



Share with colleagues



Rate this document

© Copyright 2015 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

AirPrint, iPad, iPhone, iPod touch, and Bonjour are trademarks of Apple Inc. © 2012 Google Inc. All rights reserved. Android and Google Chrome are trademarks of Google Inc. Windows is a U.S. registered trademark of the Microsoft group of companies.

4AA5-9413EEW, July 2015

