

# HP ScanJet Pro 3000 s3 Sheet-feed Scanner



Manage projects and workflows quickly and confidently. Easily handle mixed media, and get one-pass duplex scanning with speeds up to 35 ppm/70 ipm.<sup>1</sup> Scan to mobile devices for on-the-go control.<sup>2</sup> Recommended for 3,500 pages per day.



## Fast scanning. Superb results. Every page.

- Produce scans at up to 35 ppm/70 ipm<sup>1</sup> with two-sided scanning that captures both sides at once.
- Capture every page easily—even stacks of mixed media—with HP EveryPage and an ultrasonic sensor.<sup>3</sup>
- Free up space for work. This HP ScanJet Pro is small and slim—a modern design perfect for the desktop.
- Handle paper from 11 lb. (40 gsm) to 110 lb. (413 gsm) weight and up to 8.5 x 122 inches (21.6 x 309.9 cm).

## Optimize workflows with one-touch scanning

- Streamline routine work with one-touch scanning—create one-button, custom settings for recurring scan jobs.
- Scan images directly into applications with included and full-featured TWAIN and ISIS®.
- Easily transfer scans into editable text, secure PDF files, and more file types, using built-in OCR.
- Quickly share or archive scans directly to popular cloud destinations with HP Scan software.

## Capture business documents like a pro

- Define scan profiles for common document types, and scan to multiple destinations with HP Scan software.
- Scan directly to mobile devices with the HP JetAdvantage Capture App, and then edit and save files.<sup>2</sup>
- Capture and organize documents, business cards, and other file types with feature-rich software.



<sup>1</sup> Scan speed measured at 300 dpi (black-and-white, grayscale, and color). Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software. <sup>2</sup> Scanning from a mobile device requires the HP ScanJet Wireless Adaptor 100 (L2761A), which must be purchased separately, and the HP JetAdvantage Capture App. Download the app at [hp.com/go/documentmanagement](http://hp.com/go/documentmanagement). Wireless performance is dependent on physical environment and distance from access point and may be limited during active VPN connections. Wi-Fi Direct® scanning requires the mobile device to be connected directly to the Wi-Fi® network of the scanner. Wi-Fi and Wi-Fi Direct are registered trademarks of Wi-Fi Alliance®. <sup>3</sup> HP EveryPage is referred to as HP Precision Feed on HP ScanJet devices introduced prior to May 2013.

## HP ScanJet Pro 3000 s3 Sheet-feed Scanner Specifications Table

<b>Standard Connectivity</b>	USB 2.0 and USB 3.0 (SuperSpeed)
<b>Memory</b>	<b>Standard:</b> 512 MB
<b>Processor Speed</b>	550 MHz
<b>Media Types Supported</b>	Cut Sheet Paper, Printed Paper (Laser and ink), Pre-Punched Paper, Bank Checks, Business Cards, Freight Bills, Carbonless forms, Previously stapled media with staple removed
<b>Paper Handling</b>	<b>Auto Document Feeder Capacity:</b> 50 sheets of Xerox 4024 75 g/m <sup>2</sup> paper, transparencies
<b>What's in the box</b>	<b>L2753A</b> HP ScanJet Pro 3000 s3 Sheet-feed Scanner engine; Installation guide; Support flyer; Warranty guide; 2CDs; Power cord; USB cable; Power Adapter
<b>Product Dimensions</b>	<b>W x D x H:</b> 310 x 198 x 190 mm; 12.20 x 7.79 x 7.48 in <sup>1</sup> ; <b>Maximum:</b> 342 x 310 x 319 mm; 13.46 x 12.20 x 12.56 in
<b>Product Weight</b>	3.4 kg; 7.5 lb
<b>Warranty Features</b>	One-year bench limited warranty whole unit replacement, phone and Web support included. Warranty may vary by country as required by law. Go to <a href="http://hp.com/support">hp.com/support</a> to learn about HP world-class service and support options in your region.
<b>Control Panel</b>	Scan button, Cancel button, Power button with a LED and a LED for Error indication.
<b>Software Included</b>	HP WIA scan driver, HP TWAIN scan driver; HP Scan, HP Scanner Tools Utility, Nuance PaperPort (Win only), I.R.I.S. Readiris, I.R.I.S. Cardiris (Win only), EMC ISIS (Win only)
<b>Compatible Operating Systems</b>	OS X El Capitan 10.11, Microsoft® Windows® 10, 8.1, 8, 7: 32-bit or 64-bit
<b>Minimum System Requirements</b>	<b>PC:</b> Microsoft® Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Microsoft® Internet Explorer; Windows Vista®: (32-bit only), 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Microsoft® Internet Explorer 8; Windows® XP SP3 or higher (32-bit only); any Intel® Pentium® II, Celeron® or 233 MHz compatible processor, 850 MB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Microsoft® Internet Explorer 8; <b>MAC:</b> Apple® OS X Yosemite, OS X Mavericks, OS X Mountain Lion; 1 GB HD; Internet required; USB; Microsoft® Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Microsoft® Internet Explorer
<b>Power</b>	<b>Power Supply Type:</b> External Power Adapter; <b>Power Requirements:</b> Input Voltage range: 90 -264 VAC, Rated Frequency: 50 - 60HZ, Worldwide use; <b>Power Consumption:</b> 4.2 watts (ready), 0.7 watts (sleep), 0.1 watts (off), 0.1 watts (auto-off) <sup>2</sup>
<b>Operating Environment</b>	<b>Operating Temperature Range:</b> 10 to 35°C; <b>Recommended Operating Temperature Range:</b> 10 to 35°C; <b>Storage Temperature Range:</b> -40 to 60°C; <b>Non-Operating Humidity Range:</b> 0 to 90%RH (non-condensing); <b>Operating Humidity Range:</b> 15 to 80% RH (non-condensing); <b>Recommended Humidity Operating Range:</b> 15 to 80% RH (non-condensing)
<b>Accessories</b>	HP ScanJet Pro 3000 s3 roller replacement kit L2754A
<b>HP Service and Support Options</b>	HP 3yNbdExch SJN6310/SJPro3xxx Service; HP 3yNbdOnsiteExch SJN6310/SJPro3xxx SVC

Learn more at [hp.com](http://hp.com)

<sup>1</sup> With input and output trays folded and covers closed <sup>2</sup> Power requirements are based on the country/region where the scanner is sold. Do not convert operating voltages. This will damage the scanner and void the product warranty. <sup>3</sup> Actual speeds may vary depending on scan resolution, connectivity type, computer performance and application software.

