

HP LaserJet Pro MFP M127fn



This affordable, full-featured HP LaserJet Pro MFP is easy to install—and prints, copies, scans, and faxes. Enable easy printing from smartphones, tablets, and laptops—at work, home, or on the go—using mobile printing features.¹



Handle the essentials

- Use the simple, intuitive control panel to easily set up projects and start printing right away.
- Finish projects fast—use the 35-page automatic document feeder to make the most of your time.
- Easily copy both sides of a two-sided ID or other small document onto the front of a single-page.
- Set the pace for success with an MFP that prints, copies, and scans—fast.

Print on your terms

- Now you're wired. Share all your printer has to offer, company-wide, using 10/100 Ethernet connectivity.
- Print from your mobile device with built-in print capability or HP ePrint app and software.¹
- Print from virtually anywhere with AirPrint™.²



¹ Local printing requires mobile device and printer to be on the same network or have a direct wireless connection to printer. Wireless performance is dependent on physical environment and distance from the access point. Wireless operations are compatible with 2.4 GHz operations only. Remote printing requires an Internet connection to a HP web-connected printer. App or software may also be required. Wireless broadband use requires a separately purchased service contract for mobile devices. Check with your service provider for coverage and availability in your area. See hp.com/go/mobileprinting for more details. ² Supports OS X® Lion, OS X Mountain Lion and the following devices running iOS 4.2 or later: iPad® (all models), iPhone® (3GS or later) and iPod touch® (third generation or later). Works with HP's AirPrint-enabled printers and requires the printer be connected to the same network as your OS X or iOS device. Wireless performance is dependent on physical environment and distance from the access point. OS X, iPad, iPhone, and iPod touch are trademarks of Apple® Inc., registered in the United States and other countries. AirPrint™ and the AirPrint logo are trademarks of Apple Inc.

HP LaserJet Pro MFP M127fn Specifications Table

Functions / Multitasking Supported	Print, copy, scan, fax / Yes
Print Speed	A4: Up to 20 ppm black; ¹ First Page Out: As fast as 9.5 sec black
Print Resolution	Black (best): Up to 600 x 600 dpi
Print Technology	Laser
Print Resolution Technologies	FastRes 600; FastRes 1200
Print Cartridges Number	1 (black)
Standard Print languages	PCLm/PCLmS
Printer Smart Software Features	HP Auto-On/Auto-Off, HP ePrint, Apple AirPrint™, Embedded Web Server
Printer Management	HP Device Toolbox, Status Alerts (default install)
Scan Type / Technology	Flatbed, ADF / Contact Image Sensor (CIS)
Scan Resolution	Hardware: Up to 1200 x 1200 dpi; Optical: Up to 1200 dpi
Scan File Format	Windows Scan SW supports file format: JPG, RAW(BMP), PDF, TIFF, PNG; Mac Scan SW supports file format: TIFF, PNG, JPEG, JPEG-2000, PDF, PDF-Searchable, RTF, TXT
Scan Input Modes	Scanning via HP LaserJet scan application or TWAIN—or WIA-compliant application software
Scan Size	ADF: 216 x 356 mm; 8.5 x 14 in Maximum; 152 x 114 mm, 6 x 4.5 in Minimum; Flatbed: 216 x 297 mm; 8.5 x 11.7 in
Scan Speed	Up to 7 ppm (b&w), up to 5 ppm (color)
Bit Depth / Grayscale levels	24-bit / 256
Digital Sending Standard Features	Scan to E-mail by HP SW; scan to application by HP SW; scan to file by HP SW
Copy Speed	Black (A4): Up to 20 cpm ²
Copy Resolution	Black (text and graphics): Up to 600 x 600 dpi; Up to 600 x 600 dpi
Maximum Number Of Copies	Up to 99 copies
Copier Resize	25 to 400%
Copier Settings	Number of copies; Lighter/Darker; Reduce/Enlarge; Optimize (draft, text, mixed, picture); Paper Size, Collation
Fax Speed	Up to: 33.6 kbps ³
Fax Resolution	Black (best): Up to 300 x 300 dpi; Black (standard): 203 x 98 dpi
Fax Smart Software Features	Fax address book; LAN/Internet fax; Speed-dial; TAM interface
Fax Features	Fax Memory: Up to 500 pages; Auto Fax Reduction Supported: Yes; Auto-Redialing: Yes; Fax Delayed Sending: Yes; Distinctive Ring Detection Supported: Yes; Fax Forwarding Supported: Yes; Fax Phone TAM Interface Supported: Yes; Fax Polling Supported: Yes; Fax Telephone Mode Supported: Yes; Junk Barrier Supported: Yes; Maximum Speed Dialing Numbers: Up to 100 numbers; PC Interface Supported: Yes; Remote Retrieval Capability Supported: Yes; Telephone Handset Supported: No
Standard Connectivity	Hi-Speed USB 2.0 port; built-in Fast Ethernet 10/100Base-TX network port
Network Capabilities	Via built-in 10/100Base-T TCP/IP networking
Network Ready	Standard (built-in Ethernet)
Wireless Capability	No
Mobile Printing Capability	HP ePrint, Apple AirPrint™, Mobile Apps ⁴
Memory	Standard: 128 MB; Maximum: 128 MB
Processor Speed	600 MHz
Duty Cycle	Monthly, A4: Up to 8000 pages ⁵
Recommended Monthly Page Volume	250 to 2000 ⁶
Media Types Supported	Paper (plain, LaserJet), envelopes, transparencies, labels, postcards
Media Weight Supported	60 to 163 g/m ²
Media Sizes Supported	A4; A5; B5-Japanese; envelopes (ISO DL, C5, B5, Com #10, Monarch #7 3/4); 16K; post cards (Standard #10, JIS single and double)
Media Sizes Custom	76 x 127 to 216 x 356 mm
Paper Handling	150-sheet input tray; 100-sheet face-down bin; Duplex Options: Manual (driver support provided); Auto Document Feeder Capacity: Standard, 35 sheets; Envelope Feeder: Yes, 10 (in Tray 1); Standard Paper Trays: 1; Input Capacities: Up to 150 sheets standard; Up to 10 envelopes; Output Capacities: Up to 100 sheets standard; Up to 10 envelopes; Up to 75 sheets transparencies
What's in the box	CZ181A HP LaserJet Pro MFP M127fn; Preinstalled introductory HP LaserJet Black Cartridge (~700 pages); Installation guide, Getting Started guide, User's Guide, Support flyer, Warranty guide; Printer software and documentation on CD; power cord; Phone cord
Replacement Cartridges	HP 83A Black LaserJet Toner Cartridge (~1500 yield) CF283A ⁷

Product Dimensions	W x D x H: 420 x 365 x 309 mm; 16.5 x 14.4 x 12.2 in; Maximum: 420 x 438 x 309 mm; 16.5 x 17.2 x 12.2 in
Product Weight	9.1 kg; 20 lb ⁸
Warranty Features	One-year limited warranty
Energy Efficiency Compliance	ENERGY STAR [®] qualified
Control Panel	2-line LCD; Buttons (Up, Down, OK, Cancel, Back, Setup, Number of Copy, Dark/Light, Mono copy, Copy Menu, ePrint, Start Fax, Fax Setup, Number Key 0-9, *-@, #,., Power); 3 LED indicator lights (Attention, Ready, Power)
Display Description	2-line LCD (text)
Software Included	Windows: HP Installer/Uninstaller, HP PCLmS print driver, HP WIA Scan Driver, HP TWAIN Scan Driver, HP Scan, HP Fax Setup Wizard, HP Send Fax, Status Alerts, HP Update, DXP; Mac: HP Installer/Uninstaller, HP PCLmS driver, HP Scan, HP Setup Assistant, HP Fax Print Driver, HP Utility, HP Alerts, HP Firmware Updater
Fonts and Typefaces	Depend on OS fonts and typefaces
Compatible Operating Systems	Full software installs supported on: Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit), Windows XP (32-bit) (SP2 or higher); Driver only installs supported on: Windows Server 2012, Windows Server 2008 (32-bit), Windows Server 2008 (Standard Edition), Windows Server 2008 (Enterprise Edition), Windows Server 2003 (32-bit) (SP1 or higher); Mac OS X v 10.6.8 or higher; Linux: Please check Linux on-line support: http://openoffice.org/office/updates/updates.html ⁹
Compatible Network Operating Systems	Full software installs supported on: Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit), Windows XP (32-bit) (SP2 or higher); Driver only installs supported on: Windows Server 2012, Windows Server 2008 (32-bit), Windows Server 2008 (Standard Edition), Windows Server 2008 (Enterprise Edition), Windows Server 2003 (32-bit) (SP1 or higher); Mac OS X v 10.6.8 or higher; Linux: Please check Linux on-line support: http://openoffice.org/office/updates/updates.html
Minimum System Requirements	PC: Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit), Windows XP (32-bit) (SP2 or higher); 200 MB hard disk space required (CD and Web Package); 400 MB hard disk space required; 512 MB RAM installed; CD-ROM/DVD or Internet; USB or Network port; MAC: Mac OS X v 10.6; PowerPC G4, G5, or Intel® Core™ Processor; 500 MB available hard disk space; CD-ROM/DVD-ROM or Internet; USB or Network port
Power	Power Supply Type: Built-in power supply; Power Requirements: Input voltage: 110 to 127 VAC (+/- 12%), 60 Hz (+/- 3 Hz); Input voltage: 220 to 240 VAC (+/- 12%), 50/60 Hz (+/- 3 Hz) (Not dual voltage, power supply varies by part number with # Option code identifier); Power Consumption: 480 watts (Printing), 186 watts (Copying from ADF), 4.5 watts (Ready), 1.1 watts (Sleep/Auto-Off), 0.1 watts (Manual Off) ¹⁰
Acoustics	Acoustic Power Emissions: 6.0 B(A); Acoustic Pressure Emissions: 49 dB(A) ¹¹
Operating Environment	Operating Temperature Range: 15 to 32.5°C; Recommended Operating Temperature: 17.5 to 25°C; Storage Temperature Range: -20 to 60°C; Non-Operating Humidity Range: 10 to 90% RH; Operating Humidity Range: 10 to 80% RH; Recommended Humidity Operating Range: 30 to 70% RH
Security Management	Password-protected network embedded Web server; SNMPv1 community password change
Accessories	HP 1200w NFC/Wireless Mobile Print Accessory E5K46A
HP Service and Support Options	UH763E - HP 2 year Care Pack w/Return to Depot Support for LaserJet Printers; UH764E - HP 3 year Care Pack w/Return to Depot Support for LaserJet Printers; UH766PE - HP 1 year Post Warranty Care Pack w/Return to Depot Support for LaserJet Printers; HC346PE - HP 1 year User Assistance Service for Printers

Learn more at hp.com

¹Measured using ISO/IEC 24734, excludes first set of test documents. For more information see hp.com/products/1/ISO/MMDPPP/index.html. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ²First Copy Out and Copy Speed measured using ISO/IEC 29183, excludes first set of test documents. For more information see hp.com/products/1/ISO/digital_copy/index.html. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ³Based on standard ITU-T test image #1 at standard resolution. More complicated pages or higher resolution will take longer and use more memory. ⁴May require a firmware upgrade to be compatible, download at hp.com/go/support ⁵Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups. ⁶HP recommends that the number of pages per month of imaged output be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period. ⁷Replacement cartridge average declared yield ~1500 pages based on ISO/IEC 19752 and continuous print. Actual yields vary considerably based on images printed and other factors. For more information, visit: hp.com/go/learnaboutsupplies ⁸With print cartridges ⁹Driver only installs supported on: Windows Server 2012; Windows Server 2008 (32-bit), Windows Server 2008 (Standard Edition), Windows Server 2008 (Enterprise Edition), Windows Server 2003 (32-bit) (SP1 or higher) ¹⁰Values subject to change. Power numbers are the highest values measured using all standard voltages. See hp.com/support for current information. Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. ¹¹Acoustic values are subject to change. For current information see hp.com/support. Configuration tested: LaserJet Pro MFP M127fn, simplex printing with A4 paper. LaserJet Pro MFP M127fw, ADF copy and print simplex using A4 paper.

