

# HP 1200w NFC/Wireless Mobile Print Accessory



An easy solution to enable printing from mobile devices<sup>1,2</sup>



## An easy solution for printing on the move

- Make wireless direct printing easy for everyone in your office<sup>1</sup>.
- Get secure wireless printing from smartphones, tablets and laptops, using a wireless direct connection – no need for a router or network connection<sup>2</sup>.
- Compatible with up to 5 simultaneous users.

## Get convenient mobile printing at a touch

- Simply touch your mobile device to the accessory and start printing<sup>3</sup>.
- Enable touch-to-print convenience from NFC-capable mobile devices<sup>3</sup>.

## Enjoy simple and fast installation

- Get up and running fast with easy USB plug-and-play installation.
- Connecting mobile device users to your office printers or MFPs is as simple as attaching this HP Mobile Print Accessory through a USB port<sup>1</sup>.

## Go mobile and stay secure.

- Keep your network out of reach: The HP Mobile Print Accessory supports wireless direct printing and touch-to-print from mobile devices.
- Peer-to-peer connection allows mobile users to print without accessing the company network<sup>2</sup>.

<sup>1</sup> HP Mobile Print Accessory works with most HP LaserJet printers and multifunction printers (MFPs) introduced in 2008 or later that are equipped with a USB port.

<sup>2</sup> Mobile device needs to be connected directly to the WiFi network of a wireless direct-capable printer prior to printing. Depending on mobile device, an app or driver may also be required. Wireless performance is dependent on physical environment and distance from the access point in the printer.

<sup>3</sup> Mobile device must support near field communications-enabled printing (NFC), currently compatible with HP ElitePad and Samsung galaxy Note 3. For more information, see [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting).

# HP 1200w NFC/Wireless Mobile Print Accessory

## Technical specifications

### What's in the box

E5K46A	HP 1200w NFC/Wireless Mobile Print Accessory; Power adapter; Power adapter plug; USB cable; Install Guide
--------	---

### Compatibility

Operating systems	Windows 8 (64-bit), Windows 8, Windows 7 (64-bit), Windows 7, Windows Vista (64-bit), Windows Vista; Android 4.3, 4.2.x, 4.1.x, 4.0.4, 4.0.3, 3.2, 2.3.7 - 2.3.3, iOS (Apple)
-------------------	---

Printer supported	HP Color LaserJet Printer series: CP1025, CP1215, CP1515, CP1525, CP2025, CP3525, CP4025, CP4525, CP5525, CP6015; HP Mono LaserJet Printer series: P1000, P1102, P1566, P1606, P2035, P2055, P3015, P4014, P4015, P4515; HP Color Multifunctional LaserJet Printer series: Pro 100 MFP, Pro M175 MFP, Pro M251 MFP, Pro M276 MFP, Pro M451 MFP, Pro M475 MFP, CM1312 MFP, CM1415 MFP, CM2320 MFP, CM3530 MFP, CM4540 MFP, CM6030 MFP, CM6040 MFP; HP Mono Multifunction LaserJet Printer series: Pro M401 MFP, Pro M425 MFP, M1120 MFP, M1132 MFP, M1212 MFP, M1319 MFP, M1522 MFP, M1536 MFP, M4349 MFP, M4555 MFP, M9040 MFP, M9050 MFP; HP Officejet Printer series: Officejet 100, Officejet 150
-------------------	--

Browsers supported	EWS: Internet Explorer 6.0 or higher; Mozilla 2.x or higher; Firefox 2.x or higher; Safari; Chrome
--------------------	--

### Connectivity

Interfaces (standard)	Hi-Speed USB 2.0
-----------------------	------------------

### Memory

Standard	128 MB
----------	--------

Flash	128 MB
-------	--------

### Environmental ranges

Operating temperature	0 to 45°C
-----------------------	-----------

Recommended operating temperature	0 to 40°C
-----------------------------------	-----------

Storage temperature	-40 to 70°C
---------------------	-------------

Operating humidity	15 to 95% RH
--------------------	--------------

Storage humidity	15 to 95% RH
------------------	--------------

### Print Server Specifications

Network types	Wireless (802.11b/g/n)
---------------	------------------------

Print server type	External
-------------------	----------

Embedded Web Server	Yes
---------------------	-----

Install, configure, and manage with HP Web Jetadmin	No
---	----

Upgradeable firmware	Yes
----------------------	-----

Security management description	None
---------------------------------	------

### Dimensions (w x d x h)

Product dimensions	67.5 x 111.2 x 27.5 mm
--------------------	------------------------

Packaged	192 x 144 x 65 mm
----------	-------------------

### Weight

Product weight	0.08 kg
----------------	---------

Packaged	0.39 kg
----------	---------

### Power consumption

Maximum	2.5 watts maximum
---------	-------------------

Power requirements	Input voltage: 100 to 240 VAC (+/- 10%), 50/60 Hz (+/- 3 Hz)
--------------------	--

Power supply type	External universal power adapter
-------------------	----------------------------------

### Certification

Safety	IEC60950-compliant; safety UL listed; EU LVD and EN 60950 compliant; Russia GOST
--------	--

Electromagnetic	FCC CFR 47 Part 15 Class-B/ ICES-003 Issue 4: 2004, EN 301 489-17, EN55022, EN 55024, EN 61000-3-2, EN 61000-3-3
-----------------	--

Telecom compliance	FCC 15.247; EN 300-328; RSS210
--------------------	--------------------------------

Environmental specifications	Device is compliant with BFR/PVC free environmental standards.
------------------------------	--

### Warranty

One-year, limited warranty; product exchange. Warranty and support options vary by product, country and local legal requirements.
---



For more information, please visit

© 2013 Hewlett-Packard Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

4AA5-0778EEE Published in EMEA January 2014