

# HP LaserJet Pro MFP M125nw



This affordable HP LaserJet Pro MFP is easy to install and delivers crisp, clear documents. Print, copy, and scan with one, compact device that fits neatly into small office spaces.



## Extend your printing reach

- Spread printing across the office. Set up anywhere with built-in wireless printing.<sup>5</sup>
- Keep up with the pace of business—print, copy, and scan at high speeds.

## Print on your terms

- Print from virtually anywhere—using your smartphone, tablet, and PC—with Apple® AirPrint™.<sup>3</sup>
- Connect to your wireless printer in a snap, using wireless direct printing.<sup>2</sup>
- Print from your mobile device with built-in print capability or HP ePrint app and software.<sup>4</sup>

## Handle the essentials

- Speed through document tasks. Set the pace for success with an MFP that prints, copies, and scans—fast.
- Easily copy both sides of a two-sided ID or other small document onto the front of a single-page.
- Just start printing, quick and easy—with the simple control panel.



<sup>2</sup> An app or driver may be required to use HP wireless direct. For more information, see [hpconnected.com](http://hpconnected.com). Wireless performance is dependent on physical environment and distance from access point. <sup>3</sup> Supports OS X® Lion, OS X Mountain Lion and the following devices running iOS 4.2 or later: iPad® (all models), iPhone® (3GS or later) and iPod touch® (third generation or later). Works with HP's AirPrint-enabled printers and requires the printer be connected to the same network as your OS X or iOS device. Wireless performance is dependent on physical environment and distance from the access point. OS X, iPad, iPhone, and iPod touch are trademarks of Apple® Inc., registered in the United States and other countries. AirPrint™ and the AirPrint logo are trademarks of Apple Inc. <sup>4</sup> Local printing requires mobile device and printer to be on the same network or have a direct wireless connection to printer. Wireless performance is dependent upon physical environment and distance from access point. Wireless operations are compatible with 2.4 GHz operations only. Remote printing requires an internet connection to a HP web-connected printer. App or software may also be required. Wireless broadband use requires separately purchased service contract for mobile devices. Check with service provider for coverage and availability in your area. See [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting) for more details. <sup>5</sup> Wireless performance is dependent on physical environment and distance from the printer.

## HP LaserJet Pro MFP M125nw Specifications Table

<b>Functions / Multitasking Supported</b>	Print, copy, scan / Yes
<b>Print Speed</b>	<b>A4:</b> Up to 20 ppm; <b>Letter:</b> Up to 21 ppm black; <sup>1</sup> <b>First Page Out:</b> As fast as 9.5 sec black
<b>Print Resolution</b>	<b>Black (best):</b> Up to 600 x 600 dpi
<b>Print Technology</b>	Laser
<b>Print Resolution Technologies</b>	FastRes 600; FastRes 1200
<b>Print Cartridges Number</b>	1 (black)
<b>Standard Print Languages</b>	PCLm/PCLmS
<b>Printer Smart Software Features</b>	HP Auto-On/Auto-Off, HP ePrint, Apple AirPrint™, Wireless direct printing, Embedded Web Server
<b>Printer Management</b>	HP Device Toolbox; Status Alerts (default install)
<b>Scan Type / Technology</b>	Flatbed / Contact Image Sensor (CIS)
<b>Scan Resolution</b>	<b>Hardware:</b> Up to 1200 x 1200 dpi; <b>Optical:</b> Up to 1200 dpi
<b>Scan File Format</b>	Windows Scan Software supports file format: JPG, RAW (BMP), PDF, TIFF, PNG; Mac Scan SW supports file format: TIFF, PNG, JPEG, JPEG-2000, PDF, PDF-Searchable, RTF, TXT
<b>Scan Input Modes</b>	Solution Center Lite (Windows Vista, Windows XP) or Device Stage (Windows 7, Windows 8); TWIN-compliant or WIA-compliant software
<b>Scan Size</b>	<b>Flatbed:</b> 216 x 297 mm; 8.5 x 11.7 in
<b>Scan Speed</b>	Up to 7 ppm (b&w), up to 5 ppm (color)
<b>Bit Depth / Grayscale levels</b>	24-bit / 256
<b>Digital Sending Standard Features</b>	Scan to E-mail by HP Software; Scan to application by HP Software ; Scan to file by HP Software
<b>Copy Speed</b>	<b>Black (A4):</b> Up to 20 cpm; <b>Color (A4):</b> <sup>2</sup>
<b>Copy Resolution</b>	<b>Black (text and graphics):</b> Up to 300 x 300 dpi; Up to 400 x 600 dpi; <b>Color (text and graphics):</b> Up to 400 x 600 dpi
<b>Maximum Number Of Copies</b>	Up to 99 copies
<b>Copier Resize</b>	25 to 400%
<b>Copier Settings</b>	Number of copies; Lighter/Darker; Reduce/Enlarge; Optimize (draft, text, mixed, picture); Paper Size
<b>Standard Connectivity</b>	Hi-Speed USB 2.0 port; built-in Fast Ethernet 10/100Base-TX network port; Wireless 802.11b/g/n
<b>Network Capabilities</b>	Via built-in 10/100 Base-TX networking
<b>Network Ready</b>	Standard (built-in Fast Ethernet, WiFi 802.11b/g/n)
<b>Wireless Capability</b>	Yes, built-in WiFi 802.11b/g/n
<b>Mobile Printing Capability</b>	HP ePrint, Wireless direct printing, Apple AirPrint™
<b>Memory</b>	<b>Standard:</b> 128 MB; <b>Maximum:</b> 128 MB
<b>Processor Speed</b>	600 MHz
<b>Duty Cycle</b>	<b>Monthly, A4:</b> Up to 8000 pages <sup>3</sup>
<b>Recommended Monthly Page Volume</b>	250 to 2000 <sup>4</sup>
<b>Media Types Supported</b>	Paper (plain, LaserJet), envelopes, transparencies, labels, postcards
<b>Media Weight Supported</b>	60 to 163 g/m <sup>2</sup>
<b>Media Sizes Supported</b>	A4; A5; B5-Japanese; envelopes (ISO DL, C5, B5, Com #10, Monarch #7 3/4); 16K; post cards (Standard #10, JIS single and double)
<b>Media Sizes Custom</b>	76 x 127 to 216 x 356 mm
<b>Paper Handling</b>	150-sheet input tray; 100-sheet face-down bin; <b>Duplex Options:</b> Manual (driver support provided); <b>Auto Document Feeder Capacity:</b> None; <b>Envelope Feeder:</b> No; <b>Standard Paper Trays:</b> 1; <b>Input Capacities:</b> Up to 150 sheets standard; Up to 10 envelopes; <b>Output Capacities:</b> Up to 100 sheets standard; Up to 10 envelopes; Up to 75 sheets transparencies
<b>What's in the box</b>	<b>C2173A</b> HP LaserJet Pro MFP M125nw; Preinstalled introductory HP LaserJet Black Cartridge (~700 pages); Installation guide, Getting Started guide, User's Guide, Support flyer, Warranty guide; Printer software and documentation on CD; Power cord; USB cable
<b>Replacement Cartridges</b>	HP 83A Black LaserJet Toner Cartridge (~1500 yield) CF283A <sup>5</sup>

<b>Product Dimensions</b>	<b>W x D x H:</b> 420 x 365 x 254 mm; 16.5 x 14.4 x 10 in. <b>Maximum:</b> 420 x 438 x 254 mm; 16.5 x 17.2 x 10 in
<b>Product Weight</b>	8.0 kg; 17.6 lb
<b>Warranty Features</b>	One-year unit exchange warranty. Warranty and support options vary by product, country and local legal requirements. Go to <a href="http://www.hp.com/support">http://www.hp.com/support</a> to learn about HP award winning service and support options in your region.
<b>Energy Efficiency Compliance</b>	ENERGY STAR® qualified
<b>Control Panel</b>	2-line LCD; Buttons (Up, Down, OK, Cancel, Back, Setup, Number of Copy, Dark/Light, Mono copy, Copy Menu, ePrint, Wireless, Power) ; 4 LED indicator lights (Attention, Ready, Power, Wireless)
<b>Display Description</b>	2-line LCD (text)
<b>Software Included</b>	Windows: HP Installer/Uninstaller, HP PCLmS print driver, HP WIA Scan Driver, HP TWIN Scan Driver, HP Scan, Status Alerts; HP Update, EXP, Mac: HP Installer/Uninstaller, HP PCLmS Print Driver, HP Scan, HP Setup Assistant, HP Utility, HP Alerts, HP Firmware Updater
<b>Fonts and Typefaces</b>	Depend on OS fonts and typefaces
<b>Compatible Operating Systems</b>	Full software installs supported on: Windows 10 (32-bit/64-bit), Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit), Windows XP (32-bit/64-bit), Windows XP (32-bit (SP2 or higher); Driver only installs supported on: Windows Server 2012; Windows Server 2008 (32-bit), Windows Server 2008 (Standard Edition), Windows Server 2008 (Enterprise Edition), Windows Server 2003 (32-bit) (SP1 or higher); Mac OS X v 10.6.8 or higher; Linux: Please check Linux on-line support: <a href="http://www.hpippopensource.com/hplip-web/install.html">http://www.hpippopensource.com/hplip-web/install.html</a> <sup>6</sup>
<b>Compatible Network Operating Systems</b>	Full software installs supported on: Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit), Windows XP (32-bit) (SP2 or higher); Driver only installs supported on: Windows Server 2012; Windows Server 2008 (32-bit), Windows Server 2008 (Standard Edition), Windows Server 2008 (Enterprise Edition), Windows Server 2003 (32-bit) (SP1 or higher); Mac OS X v 10.6.8 or higher; Linux: Please check Linux on-line support: <a href="http://www.hpippopensource.com/hplip-web/install.html">http://www.hpippopensource.com/hplip-web/install.html</a>
<b>Minimum System Requirements</b>	<b>PC:</b> Windows 10 (32-bit/64-bit), Windows 8 (32-bit/64-bit), Windows 7 (32-bit/64-bit), Windows Vista (32-bit/64-bit), Windows XP (32-bit) (SP2 or higher); 200 MB available hard disk space required (CD and Web Package); 400 MB available hard disk space required; 512 MB RAM installed; CD-ROM/DVD or Internet; USB or Network port; <b>MAC:</b> Mac OS X v 10.6; PowerPC G4, G5, or Intel® Core™ Processor; 500 MB available hard disk space; CD-ROM/DVD-ROM or Internet; USB or Network port
<b>Power</b>	<b>Power Supply Type:</b> Built-in power supply; <b>Power Requirements:</b> Input voltage: 110 to 127 VAC (+/- 12%), 60 Hz (+/- 3 Hz); Input voltage: 220 to 240 VAC (+/- 12%), 50/60 Hz (+/- 3 Hz) (Not dual voltage, power supply varies by part number with # Option code identifier); <b>Power Consumption:</b> 465 watts (Printing), 110 watts (Copying), 2.2 watts (Ready), 0.7 watts (Sleep/Auto-Off), 0.2 watts (Manual Off) <sup>7</sup>
<b>Acoustics</b>	<b>Acoustic Power Emissions:</b> 6.1 B(A); <b>Acoustic Pressure Emissions:</b> 48 dB(A) <sup>8</sup>
<b>Operating Environment</b>	<b>Operating Temperature Range:</b> 15 to 32.5°C; <b>Recommended Operating Temperature:</b> 17.5 to 25°C; <b>Storage Temperature Range:</b> -20 to 60°C; <b>Non-Operating Humidity Range:</b> 10 to 90% RH; <b>Operating Humidity Range:</b> 10 to 80% RH; <b>Recommended Humidity Operating Range:</b> 30 to 70% RH
<b>Security Management</b>	Password-protected network embedded Web server; 802.11 i: WEP, WPA, WPA2; SNMPv1 community password change
<b>HP Service and Support Options</b>	UH764E - HP 3 years Return Consumer LaserJet MFP-E SVC; UH763E - HP 2 years Return Consumer LaserJet MFP-E SVC; UH766PE - HP 1 year Post Warranty Return Consumer LaserJet MFP-E SVC

Learn more at [hp.com](http://hp.com)

<sup>1</sup>Measured using ISO/IEC 24734, excludes first set of test documents. For more information see [hp.com/products/1/ISO/MMDPP/index.html](http://hp.com/products/1/ISO/MMDPP/index.html). Exact speed varies depending on the system configuration, software application, driver, and document complexity. <sup>2</sup>First Copy Out and Copy Speed measured using ISO/IEC 29183, excludes first set of test documents. For more information see [hp.com/products/1/ISO/digital\\_copy/index.html](http://hp.com/products/1/ISO/digital_copy/index.html). Exact speed varies depending on the system configuration, software application, driver, and document complexity. <sup>3</sup>Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups. <sup>4</sup>HP recommends that the number of pages per month of imaged output be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period. <sup>5</sup>Replacement cartridge average declared yield ~1500 pages based on ISO/IEC 19752 and continuous print. Actual yields vary considerably based on images printed and other factors. For more information, visit: [hp.com/go/learnaboutsupplies](http://hp.com/go/learnaboutsupplies) <sup>6</sup>Driver only installs supported on: Windows Server 2012; Windows Server 2008 (32-bit), Windows Server 2008 (Standard Edition), Windows Server 2008 (Enterprise Edition), Windows Server 2003 (32-bit) (SP1 or higher) <sup>7</sup>Values subject to change. Power numbers are the highest values measured using all standard voltages. See [hp.com/support](http://hp.com/support) for current information. Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. <sup>8</sup>Measured according to ISO 7779 and declared in accordance with ISO 9296; values are subject to change. For current information, see [hp.com/support](http://hp.com/support). Configuration tested: LaserJet Pro MFP M125nw printing simplex on A4 paper.

