

HP t310 Quad-Display Zero Client



Expand your view and productivity with a quad-display Zero Client

Multi-task like a pro and get simple, secure, workstation-class PCoIP performance for all your design, content creation, and business applications with the HP t310 Quad-Display Zero Client, the newest HP Zero Client, which supports up to four displays.¹



Master multi-tasking in stunning resolution

- See and share all your projects on a DisplayPort-enabled multi-display¹ setup—no hubs or adapters required. Now you can run multiple graphics, modeling, and simulation feeds on two 2560 x 1600 displays or four 1920 x 1200 displays.

Worry-free security

- Secure your work with a Teradici Zero Client that has no OS and transmits pixels instead of data. Say goodbye to patches, updates, and viruses. Plus, low noise, heat, and power consumption mean the hardware's easy to maintain, too.

Powerful performance

- Experience high-resolution, full-frame rate 3D graphics and HD streaming media across all your displays¹ from the accelerated performance of PCoIP hardware. Connect quickly to your USB devices, and send and receive HD audio without any lags.

Additional features:

- Get your users to work right away, whatever the task—full-blown VDI, local software applications, video rendering to quad displays¹ or all the above—with a true driverless and stateless Zero Client.
- Use your HP t310 with VMware[®] Horizon 6¹ to give your users an optimized, on-demand, secure virtual workspace for remote desktops, applications, and video streams on a single, efficient platform.
- Compatibility with Amazon WorkSpaces¹ enables easy provisioning of cloud-based desktops so your users can access their documents, applications, resources, and more.
- Stay in contact with colleagues with support for unified communications (UC) solutions.¹
- Enjoy flexible network connectivity with the standard RJ-45 interface or an optional Fiber Optic network adapter.¹
- Keep your cabling clean with all the connections you need and none you don't—four DisplayPort outputs, four USB 2.0, and audio, mic, and speaker jacks.
- Rest easy with a three-year limited warranty and HP Care service options.²

HP t310 Quad-Display Zero Client Specifications Table



Available Operating System	Operating system independent
Available Processors	TERA2140 PCoIP Zero Client
Maximum Memory	Up to 512 MB DDR3-1333 SDRAM Standard memory note: Transfer rates up to 1333 MT/s
Available Graphics	Graphics integrated on processor
Audio	1/8-inch mini-jack with 16, 20, 24, or 32-bit stereo and 8-96 kHz sample rate (output). 1/8-inch mini-jack with 16, 20, 24, or 32-bit stereo and 96 kHz sample rate (input).
Communications	10/100/1000 GbE; 100 Mbps Fiber NIC (optional); 1 Gbps Fiber NIC (optional); Wake on LAN (WOL) using magic packet; Wake on USB; TCP/IP with DNS and DHCP; UDP
Protocols	VMware® Horizon View™ through PCoIP; VMware Horizon® DaaS® through PCoIP; Amazon WorkSpaces through PCoIP ^{1,2}
Input Device	HP USB Keyboard HP USB Mouse
Ports and Connectors	2 USB 2.0; 1 microphone jack; 1 headphone jack (1 each of 4 USB 2.0 ports are used for keyboard and mouse)
Dimensions	4.48 x 13.25 x 18.3 cm (Without stand)
Weight	Starting at 0.802 kg
Power	36 W, worldwide auto-sensing, 100-240 VAC, 50-60 Hz
Warranty	3-year (3-3-0) limited warranty and service offering includes 3 year of unit exchange with no on-site repair. Terms and conditions vary by country. Certain restrictions and exclusions apply.

HP t310 Quad-Display Zero Client

Accessories and services (not included)

HP DisplayPort To VGA
Adapter



Converts the DisplayPort connector on a HP Compaq Business Desktop computer to a VGA port.
Product number: AS615AA

HP DisplayPort to DVI-D
Adapter



Converts the DisplayPort connector on a HP Compaq Business Desktop computer to a single link DVI-D port. The adapter has a latching DisplayPort connector on one end and DVI-D connector on the other for connecting to a DVI-D monitor cable.
Product number: FH973AA

HP DisplayPort to HDMI 1.4
Adapter for PC



Make the most of the available ports on your HP Business Desktop or HP Workstation with the HP DisplayPort to HDMI 1.4 Adapter, which converts your PC's DisplayPort output to HDMI for quick and easy connection to a range of multimedia devices.¹
Product number: K2K92AA

HP DisplayPort Cable Kit



Connects a DisplayPort connector on an HP Business Desktop computer to a DisplayPort connector on a monitor.
Product number: VN567AA

HP 5 year Next Business Day
Advanced Exchange
Hardware Support for Thin
Clients



HP provides quick replacement of your failed hardware unit the day after it goes down, if the problem can't be resolved remotely, for 5 years.
Product number: U7929E

Learn more at
www.hp.eu/hpoptions

HP t310 Quad-Display Zero Client

Messaging Footnotes

¹ Sold separately.

² HP Care Packs are sold separately. Service levels and response times for HP Care Packs may vary depending on your geographic location. Service starts on date of hardware purchase. Restrictions and limitations apply. For details, visit www.hp.com/go/cpc. HP Services are governed by the applicable HP terms and conditions of service provided or indicated to Customer at the time of purchase. Customer may have additional statutory rights according to applicable local laws, and such rights are not in any way affected by the HP terms and conditions of service or the HP Limited Warranty provided with your HP Product.

Technical specifications disclaimers

¹ Amazon WorkSpaces requires subscription from Amazon. See <http://aws.amazon.com/workspaces/> for complete details.

² VMware is sold separately, subscription required.

Learn more at

www.hp.eu/thinclient

Engage HP Financial Services

Explore monthly payment options and technology refresh plans that can provide more flexibility to help you meet your IT goals. More information on www.hp.com/go/hpfs.

Sign up for updates

www.hp.com/go/getupdated

© Copyright 2016 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. All trademarks are the property of their respective owners.

4AA6-8833EEE, November 2016

