

# HP LaserJet Pro MFP M132 series



Keep things simple with a wireless HP LaserJet Pro MFP powered by JetIntelligence Toner cartridges.

Print professional documents from a range of mobile devices,<sup>1</sup> plus scan, copy, and help save energy with a wireless MFP designed for efficiency.



HP LaserJet Pro MFP M132a



HP LaserJet Pro MFP M132nw



HP LaserJet Pro MFP M132snw

## Designed for efficiency

- Print, scan, and copy with HP's smallest LaserJet MFP—designed to fit into tight workspaces.
- Wait less with an HP LaserJet Pro that prints faster than its predecessor<sup>2</sup>—up to 22 pages per minute.<sup>3</sup>
- Help save energy with HP Auto-On/Auto-Off Technology.<sup>7</sup>

## Mobile printing made simple<sup>11</sup>

- Print from iPhone® and iPad® with AirPrint® 1.5, which automatically scales jobs to the correct paper size.<sup>3</sup>
- Print with the ease of sending an email, right from a smartphone, tablet, or notebook, using HP ePrint.<sup>9</sup>
- Print directly from your mobile device to your Wi-Fi Direct® printer—without accessing the company network.<sup>4</sup>
- Send jobs from your smartphone, tablet, or PC to any company printer, using Google Cloud Print™ 2.0.<sup>9</sup>

## HP quality—print after print

- Produce sharp text, bold blacks, and crisp graphics with precision black toner.
- Don't be fooled by alternatives that mimic Original HP. Anti-fraud technology can help ensure you're getting the quality you paid for.
- Track remaining pages with print gauge technology, and get more pages than ever with page maximizer technology.
- No delays or mess—quickly replace your cartridges, using auto seal removal and easy-open packaging.

## Product walkaround

1. 35-sheet automatic document feeder (M132snw model only)
2. Flatbed scanner handles sheets up to 216 x 297 mm
3. 100-sheet output bin
4. Built-in wireless networking and Wi-Fi Direct® printing (M132nw/M132snw only)
5. Power on/off button
6. Top cover access to toner cartridges
7. 150-sheet input tray with dust cover
8. 2-line LCD control panel (Icon LCD on M132a model)
9. 600 MHz processor, 256 MB RAM (128 MB for M132a model)
10. Hi-Speed USB 2.0 printing port
11. Fast Ethernet network port (M132nw/M132snw models only)
12. Power connection



**HP LaserJet Pro MFP M132snw**



## Series at a glance



Model	HP LaserJet Pro MFP M132a	HP LaserJet Pro MFP M132nw	HP LaserJet Pro MFP M132snw
<b>Product number</b>	G3Q61A	G3Q62A	G3Q68A
<b>Functions</b>	Print, copy, and scan	Print, copy, and scan	Print, copy, and scan
<b>Print speed (black, normal)<sup>1</sup></b>	Up to 22 pages per minute (ppm), A4	Up to 22 pages per minute, A4	Up to 22 pages per minute, A4
<b>First page out from ready</b>	As fast as 7.3 seconds	As fast as 7.3 seconds	As fast as 7.2 seconds
<b>Control panel</b>	Icon LCD	2-line LCD (text)	2-line LCD (text)
<b>Input capacity</b>	150 sheets	150 sheets	150 sheets
<b>Automatic document feeder</b>	Not available	Not available	35-sheet
<b>Networking</b>	USB connectivity only	Built-in Ethernet, Wireless 802.11b/g/n <sup>2</sup>	Built-in Ethernet, Wireless 802.11b/g/n <sup>2</sup>
<b>Mobile printing capability</b>	No	HP ePrint, <sup>3</sup> Wi-Fi Direct, <sup>4</sup> Apple AirPrint, <sup>5</sup> Google Cloud Print 2.0, <sup>6</sup> Mopria-certified	HP ePrint, <sup>3</sup> Wi-Fi Direct, <sup>4</sup> Apple AirPrint, <sup>5</sup> Google Cloud Print 2.0, <sup>6</sup> Mopria-certified

## HP Services

Downtime can have serious consequences, so HP provides support beyond the standard warranty. You benefit from reduced risk, maximized uptime, predictable service delivery and no unbudgeted repair costs.

Choose from:

### Optimized Care (optimum performance and stability):

4 hour Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

### Standard Care (high level of uptime):

Next Business Day Onsite Support, Maintenance Kit Replacement Service, Installation with Network Configuration Service

### Basic Care (minimum recommended support):

Next Business Day Onsite Support

### 4 hr Onsite Support:

Onsite support within four hours after a service call received within the coverage window

### Next Business Day Onsite Support:

Onsite service the next business day after the service call is received

### Maintenance Kit Replacement Service:

Onsite replacement of your printer's maintenance kit including parts, materials, and labor

### Installation with Network Configuration Service:

Assembly, network configuration, and basic administrator familiarization  
For more information about HP Care Pack, HP Contractual, or HP Managed Print Services, visit [hp.com/go/printservices](http://hp.com/go/printservices)



## Top Features

Help save energy. This efficient multifunction laser printer prints, scans, copies, and faxes while keeping energy costs low, so you save resources.

Mobile printing is easier than ever with HP. Print with minimal steps from a broad range of mobile devices—smartphones, tablets, and notebooks.<sup>1</sup>

Count on consistent results—Original HP Toner cartridges with JetIntelligence are designed to work flawlessly with this HP LaserJet Pro. Anti-fraud authentication helps protect your business from frustrating quality issues and costly reprints.

---

#### Product

<b>G3Q61A</b>	HP LaserJet Pro MFP M132a
<b>G3Q62A</b>	HP LaserJet Pro MFP M132nw
<b>G3Q68A</b>	HP LaserJet Pro MFP M132snw

---

#### Replacement cartridges

<b>CF218A</b>	HP 18A Black Original LaserJet Toner Cartridge (1,400 pages)
<b>CF219A</b>	HP 19A Original LaserJet Imaging Drum (12,000 pages)

---

#### HP Care Packs

<b>UH757E</b>	HP 3 year Care Pack w/Next Day Exchange for LaserJet Printers
<b>UH773E</b>	HP 3 year Care Pack w/Onsite Exchange for LaserJet Printers
<b>UH769E</b>	HP 3 year Care Pack w/Pickup and Return Support for LaserJet Printers
<b>UH764E</b>	HP 3 year Care Pack w/Return to Depot Support for LaserJet Printers

Protect your investment with HP Care Pack. Let HP certified engineers resolve your technical issues. For more details on HP Care Pack, go to [hp.com/go/cpc](http://hp.com/go/cpc)

---

#### Paper

Contact HP via phone: Asia: 65 6253 8500

---

#### Solutions

HP Web Jetadmin: [hp.com/go/wja](http://hp.com/go/wja)  
HP Universal Print Driver: [hp.com/go/upd](http://hp.com/go/upd)  
HP Imaging and Printing Security Center: [hp.com/go/ipsc](http://hp.com/go/ipsc)

---

# HP LaserJet Pro MFP M132 series

Model	HP LaserJet Pro MFP M132a	HP LaserJet Pro MFP M132nw	HP LaserJet Pro MFP M132snw
Product number	G3Q61A	G3Q62A	G3Q68A
Functions	Print, copy, scan		
<b>Print</b>			
Duplex print options	Manual duplex		
Print speed <sup>12</sup>	<b>Black (normal, A4):</b> Up to 22 ppm; <b>Black (normal, letter):</b> Up to 23 ppm; <b>Black (Landscape, A5):</b> Up to 38 ppm		
First page out <sup>14</sup>	<b>Black (A4, ready):</b> As fast as 7.3 sec; <b>Black (A4, sleep):</b> As fast as 8.1 sec	<b>Black (A4, ready):</b> As fast as 7.3 sec; <b>Black (A4, sleep):</b> As fast as 7.5 sec	<b>Black (A4, ready):</b> As fast as 7.2 sec; <b>Black (A4, sleep):</b> As fast as 7.5 sec
Print resolution	<b>Black (best):</b> Up to 600 x 600 dpi, HP FastRes 1200 (1200 dpi quality); <b>Black (normal):</b> Up to 600 x 400 dpi, HP FastRes 600 (600 dpi quality)		
Standard print languages	PCLmS, URF, PWG		
Printer management	HP Printer Assistant (UDC); HP Device Toolbox; HP Utility (Mac)		
<b>Scan</b>			
Scan type technology	<b>Type:</b> Flatbed; <b>Technology:</b> CIS		<b>Type:</b> ADF, flatbed; <b>Technology:</b> CIS
Scan speed <sup>16</sup>	<b>Normal, A4:</b> Not supported		<b>Normal, A4:</b> Up to 10 ppm
Scan resolution	<b>Hardware:</b> Up to 600 x 600 dpi (color, flatbed), Up to 1200 x 1200 dpi (mono, flatbed); <b>Optical:</b> Up to 600 dpi (color, flatbed), Up to 1200 dpi (mono, flatbed)	<b>Hardware:</b> Up to 300 x 300 dpi (color and mono, ADF); Up to 1200 x 1200 dpi (color and mono, flatbed); <b>Optical:</b> Up to 300 dpi (color and mono, ADF); Up to 1200 dpi (color and mono, flatbed)	
Digital sending standard features	No		
Color scanning	Yes		
Scan size	<b>Flatbed:</b> 215.9 x 297 mm; <b>ADF scan size:</b> No		<b>Flatbed:</b> 215.9 x 297 mm; <b>ADF scan size:</b> 215.9 x 297 mm
Scan input mode	Scanning via HP LaserJet Scan (Windows®); HP Director (Macintosh) or TWAIN-compliant or WIA-compliant software		Front control panel, scanning via HP LaserJet Software Scan or TWAIN-compliant or WIA-compliant software
Scan file format	JPG, RAW (BMP), PNG, TIFF, PDF		
<b>Copy</b>			
Copy speed <sup>15</sup>	<b>Black (normal, A4):</b> Up to 21 cpm; <b>Black (normal, letter):</b> Up to 23 cpm		
Copier smart software features	ID Copy		
First copy out	<b>Black (A4):</b> As fast as 10.1 sec; <b>Black (A4, sleep):</b> As fast as 10.9 sec; <b>Black (letter):</b> As fast as 9.6 sec; <b>Black (letter, sleep):</b> As fast as 11.3 sec	<b>Black (A4):</b> As fast as 10 sec; <b>Black (A4, sleep):</b> As fast as 10.9 sec; <b>Black (letter):</b> As fast as 9.5 sec; <b>Black (letter, sleep):</b> As fast as 10.1 sec	<b>Black (A4):</b> As fast as 7.4 sec; <b>Black (A4, sleep):</b> As fast as 7.4 sec; <b>Black (letter):</b> As fast as 7.1 sec; <b>Black (letter, sleep):</b> As fast as 7.3 sec
Copy resolution	<b>Black (text and graphics):</b> 600 x 400 dpi		
Max no of copies	Up to 99 copies		
Copier resize	25 to 400%		
Copier settings	Number of Copies; Lighter/Darker; Optimize; Paper; Multi-Page Copy; Draft Mode		Number of Copies; Lighter/Darker; Optimize; Paper; Multi-Page Copy; Draft Mode; Collation.
<b>Connectivity</b>			
Standard connectivity	Hi-Speed USB 2.0 port (device)	Hi-Speed USB 2.0 port (device); built-in Fast Ethernet 10/100Base-TX network port; Wireless	
Mobile print capability	No	Apple AirPrint™; HP ePrint; Google Cloud Print 2.0; Mopria-certified; Wi-Fi Direct®	
Wireless capability	No	Standard(WiFi 802.11b/g/n)	
Network Capabilities	No	10/100 Ethernet	
Memory	<b>Standard:</b> 128 MB; <b>Maximum:</b> 128 MB	<b>Standard:</b> 256 MB; <b>Maximum:</b> 256 MB	
Processor speed	600 MHz		
Duty cycle (monthly) <sup>9</sup>	Up to 10,000 pages; <b>Recommended monthly page volume</b> <sup>10</sup> : 150 to 1,500		
<b>Paper handling</b>			
Input	150-sheet input tray		
Output	100-sheet output tray		
Media type	Paper (laser, plain, photo, rough, vellum), envelopes, labels, cardstock, postcards		
Media weight	60 to 163 g/m²		
Media sizes custom	76 x 127 to 216 x 356 mm		
Dimensions (W x D x H)	398 x 288 x 231.1 mm		415.1 x 288 x 279.5 mm
Weight	6.8 kg		7.6 kg
What's in the box <sup>1</sup>	HP LaserJet Pro MFP M132a; HP Black LaserJet Toner Cartridge ~1,400 pages; HP LaserJet Imaging Drum ~12,000 pages; Power cord; USB cable (AP); Getting started guide; Set up poster; Support flyer; Warranty documents (CN, Indo, AU, Mex, BR, AG); Printer documentation and software on CD-ROM; Errata declaration (some countries)	HP LaserJet Pro MFP M132nw; HP Black LaserJet Toner Cartridge ~1,400 pages; HP LaserJet Imaging Drum ~12,000 pages; Power cord; USB cable; Getting started guide; Set up poster; Support flyer; Warranty documents (CN, Indo, AU, Mex, BR, AG); Printer documentation and software on CD-ROM; Errata declaration (some countries)	HP LaserJet Pro MFP M132snw; HP Black LaserJet Toner Cartridge ~1,400 pages; HP LaserJet Imaging Drum ~12,000 pages; Power cord; USB cable; Getting started guide; Set up poster; Support flyer; Warranty documents (CN, Indo, AU, Mex, BR, AG); Printer documentation and software on CD-ROM; Errata, declaration (some countries)
Warranty features	One-year limited warranty		
<b>Systems</b>			
Compatible operating systems <sup>18</sup>	Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer. Windows Vista®: (32-bit only), 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8. Windows® XP SP3 or higher (32-bit only): any Intel® Pentium® II, Celeron® or 233 MHz compatible processor, 850 MB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8. Apple® OS X Sierra(v10.12), OS X El Capitan (v10.11), OS X Yosemite (v10.10); 1 GB HD; Internet required; USB Linux (For more information, see <a href="http://hplipopensource.com/hplip-web/index.html">http://hplipopensource.com/hplip-web/index.html</a> )		
Minimum system requirements	<b>PC:</b> Windows® 10, 8.1, 8, 7: 32-bit or 64-bit, 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer; Windows Vista®: (32-bit only), 2 GB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8; Windows® XP SP3 or higher (32-bit only): any Intel® Pentium® II, Celeron® or 233 MHz compatible processor, 850 MB available hard disk space, CD-ROM/DVD drive or Internet connection, USB port, Internet Explorer 8 <b>Mac:</b> Apple® OS X Sierra(v10.12), OS X El Capitan (v10.11), OS X Yosemite (v10.10); 1 GB HD; Internet required; USB		
Security management	No	Password-protected network embedded Web server; enable/disable network ports; SNMPv1 community password change	
Control panel	ICON LCD: Dual digit numeric LCD display; Buttons (Up, Down, Cancel, Start Copy, Copy Setup); 3 LED indicator lights (Ready, Attention, Toner); Copy setting icons(Copies, Darker/Lighter, Reduce/Enlarge)	2-line LCD: 2-line LCD text display; Buttons(OK, Back, Forward/Backward, Cancel, Number of Copy, Darker/Lighter, Copy Menu , Start Copy, Main Setup, Wireless);3 light-emitting diode (LED) indicator lights (Ready, Attention, Wireless).	
Display	ICON LCD		
Power	<b>Power supply type:</b> Internal; <b>Power supply required:</b> 110-volt input voltage: 110 to 127 VAC (+/- 10%), 60 Hz/50 Hz, 4.8 A; 220-volt input voltage: 220 to 240 VAC (+/- 10%), 60 Hz/50 Hz, 2.8 A; <b>Power consumption</b> <sup>2</sup> : 255 watts (active printing), 4.2 watts (ready), 1.0 watts (sleep), 0.05 watts (Auto Off/Wake on USB, enabled at shipment), 0.05 watts (Auto-off/Manual-on), 0.05 (Manual Off); <b>Typical Electricity Consumption number</b> <sup>3</sup> : BA: 0.627 kWh/Week; ES: 0.635 kWh/Week		
Software included	For Windows OS: HP Software Installer; HP Software Uninstaller (exclude Win8+); HP PCLmS Printer Driver; HP Device Experience (DXP), HP Connected, Device Setup & Software, Online user manuals, HP Printer Assistant, HP Scan Driver; HP Scan Application, HP Product Improvement Study, For Mac OS: Welcome Screen, (Directs users to HP.com or OS App Store for LaserJet Software).		
Acoustics	<b>Acoustic Power Emissions:</b> 6.5 B(A) (printing at 22 ppm); <b>Acoustic Power Emissions (ready):</b> 2.6 B(A); <b>Acoustic Pressure Emissions Bystander (active, printing):</b> 51 dB(A); <b>Acoustic Pressure Emissions Bystander (ready):</b> 16 dB(A)		
Environmental ranges	<b>Operating Temperature Range:</b> 15 to 32.5°C; <b>Recommended Operating Temperature:</b> 17.5 to 25°C; <b>Non-operating Humidity Range:</b> 10 to 90% RH; <b>Operating Humidity Range:</b> 10 to 80% RH; <b>Recommended Operating Humidity Range:</b> 30 to 70% RH		
Safety approvals and requirements	IEC 60950-1:2005 +A1:2009+A2:2013/EN60950-1:2006 +A11:2009 +A1:2010+A12:2011+A2:2013; IEC 60825-1:2007 / EN 60825-1:2007 (Class 1 Laser/LED Product); IEC 62479:2010 / EN; 62479:2010; GB4943-2011		
Supported network protocols	No	TCP/IP; IPv4; IPv6; IP Direct Mode; LPD; SLIP; Bonjour; WS-Discovery; BOOTP/ DHCP/ AutoIP; WINS; SNMP v 1/2/3; and HTTP/HTTPS	

## Footnotes

- <sup>1</sup> App or software and HP ePrint account registration also may be required. Some features require purchase of an optional accessory. Learn more at <http://www.hp.com/go/mobileprinting>
- <sup>2</sup> Printing speed measured using ISO/IEC 24734 and excludes first set of test documents. Exact speed versus predecessor varies depending on the system configuration, software application, driver, and document complexity. Learn more at <http://www.hp.com/go/printerclaims>.
- <sup>3</sup> Mobile device must have iOS v7.0 or higher. Learn more at <http://www.hp.com/go/mobileprinting>
- <sup>4</sup> Feature is supported on select printers. Mobile device needs to be connected directly to the signal of a Wi-Fi Direct® supported MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. For details, see <http://www.hp.com/go/mobileprinting>. Wi-Fi Direct is a registered trademark of Wi-Fi Alliance®.
- <sup>5</sup> Requires Google Cloud Print™ registration and Google account. Learn more at <http://hp.com/go/mobileprinting>
- <sup>6</sup> Measured using ISO/IEC 17629. Exact speed varies depending on the system configuration, software application, driver, and document complexity. Learn more at <http://www.hp.com/go/printerclaims>.
- <sup>7</sup> HP Auto-On/Auto-Off Technology capabilities are subject to printer and settings.
- <sup>8</sup> Requires an Internet connection to the printer. Services may require registration. App availability varies by country, language, and agreements. For details, see [hpconnected.com](http://hpconnected.com).
- <sup>9</sup> Printer requires ePrint account registration. App or software may be required. Learn more at <http://www.hp.com/go/mobileprinting>
- <sup>10</sup> As compared with cartridge gauges for HP predecessor products.
- <sup>11</sup> Features are available only in selected printers.

## Product Walkaround disclaimers

- <sup>1</sup> Printing speed measured using ISO/IEC 24734 and excludes first set of test documents. Exact speed varies depending on the system configuration, software application, driver, and document complexity. For more information see [hp.com/go/printerclaims](http://www.hp.com/go/printerclaims).
- <sup>2</sup> Wireless performance is dependent on physical environment and distance from access point, and may be limited during active VPN connections.
- <sup>3</sup> Printer requires ePrint account registration. App or software may be required. Learn more at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting).
- <sup>4</sup> Mobile device needs to be connected directly to the signal of a Wi-Fi Direct® supported MFP or printer prior to printing. Depending on mobile device, an app or driver may also be required. For details, see [hp.com/go/mobileprinting](http://www.hp.com/go/mobileprinting). Wi-Fi Direct is a registered trademark of Wi-Fi Alliance®.
- <sup>5</sup> Mobile device must have iOS v7.0 or higher. Learn more at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting).
- <sup>6</sup> Requires Google Cloud Print™ registration and Google™ account. Learn more at [hp.com/go/mobileprinting](http://hp.com/go/mobileprinting).

## Technical specification disclaimers

- <sup>1</sup> HP 18A Original Black LaserJet Toner Cartridge (~1,400 pages), HP 19A Original LaserJet Imaging Drum (~12,000 pages). Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>.
- <sup>2</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115 V device.
- <sup>3</sup> Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty. Energy Star value typically based on measurement of 115 V device.
- <sup>4</sup> Based on the BA TEC method with the following possible exceptions: 1 minute or less sleep delay setting, Wi-Fi disabled.
- <sup>5</sup> Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>.
- <sup>6</sup> Declared yield value in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see <http://www.hp.com/go/learnaboutsupplies>.
- <sup>7</sup> HP SureSupply alerts you when your print cartridge is running low and helps you purchase online or locally through HP or a participating retailer. Only available with Original HP supplies; Internet access required. To learn more, visit <http://www.hp.com/go/SureSupply>.
- <sup>8</sup> Duty cycle is defined as the maximum number of pages per month of imaged output. This value provides a comparison of product robustness in relation to other HP LaserJet or HP Color LaserJet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups.
- <sup>10</sup> HP recommends that the number of printed pages per month be within the stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period.
- <sup>11</sup> Up to 22 ppm
- <sup>12</sup> Measured using ISO/IEC 24734, excludes first set of test documents. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- <sup>13</sup> Measured using ISO 24734 Feature Test, A5 Landscape Feed. Speed may vary based on content, PC, media orientation, and media type.
- <sup>14</sup> Measured using ISO/IEC 17629. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- <sup>15</sup> First Copy Out and Copy Speed measured using ISO/IEC 29183, excludes first set of test documents. For more information see <http://www.hp.com/go/printerclaims>. Exact speed varies depending on the system configuration, software application, driver, and document complexity.
- <sup>16</sup> Scan speeds measured from ADF. Actual processing speeds may vary depending on scan resolution, network conditions, computer performance, and application software.
- <sup>17</sup> HP recommends that the number of scanned pages per month be within the stated range for optimum device performance
- <sup>18</sup> Not supporting Windows® XP (64-bit) and Windows Vista® (64-bit); Not all "Compatible Operating Systems" are supported with INBOX software; Full solution software available only for Windows 7 and newer; Legacy Windows Operation Systems (XP, Vista, and equivalent servers) drivers only; For Windows Server 2003 32-bit and 2008 32-bit and 64-bit, 2008 R2 64-bit, 2012 64-bit, 2012 R2 64-bit only drivers (print/scan/fax) are installed; Windows RT OS for Tablets (32- & 64-bit) uses a simplified HP print driver built into the RT OS; Linux systems use in-OS HPLIP software

## To learn more, visit [hp.com](http://hp.com)

© Copyright 2017 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

