

Data sheet

# HP USB-A to USB-C Dongle



## A dongle that delivers universal compatibility

Give your HP notebook or mobile device access to the complete desktop experience of your HP USB-C Universal Dock with the HP USB-A to USB-C Dongle.

### Simple setup, endless connections

Plug the USB-A connector into your device's USB-A port and the USB-C™ connector to your HP USB-C Universal Dock to enjoy the dock's expanded connectivity to a wired network, dual 4K displays, and accessories.

### Keep it together

Secure the dongle to your HP USB-C Universal Dock with the included tether strap.

### World-class support

Get the reassurance of a one-year limited warranty.

## Specifications



**HP USB-A to USB-C Dongle**

<b>Part number</b>	3RV49AA
<b>Dimensions (Not including cable and USB-C plug)</b>	36.6 x 23.3 x 11mm
<b>Dimensions (Including cable and USB-C plug)</b>	138 x 23.3 x 11mm
<b>Weight</b>	17g
<b>Upstream port</b>	USB Type-A (USB 3.0) plug to host platform
<b>Downstream port</b>	USB 3.0 Type-C receptacle x1 Standard USB-C CC Logic IC integrated Standard USB-C MUX IC integrated for USB-C Reversible Function
<b>Temperature (operation)</b>	32~104 °F (0~40°C)
<b>Temperature (non-operation)</b>	-4~140 °F (-20~+60°C)
<b>Relative humidity (operation)</b>	5%~90% RH, non-condensing
<b>Relative humidity (non-operation)</b>	5%~95% RH, non-condensing
<b>Altitude (operation)</b>	10000ft (3048m)
<b>Altitude (non-operation)</b>	30000ft (9144m)
<b>Shock (operation)</b>	40G, 2ms, half-sine
<b>Shock (non-operation)</b>	240G, 2ms, half-sine
<b>Random vibration (operation)</b>	~0.21Grms, 5~500 Hz
<b>Random vibration (non-operation)</b>	~2.09Grms, 5~500 Hz, Non-Operating
<b>EMI and safety certifications</b>	TBA
<b>Compatibility</b>	HP USB-C Universal Dock

**Sign up for updates**  
[hp.com/go/getupdated](http://hp.com/go/getupdated)



Share with colleagues



Rate this document

